


R95C 8-Port 2-Channel Discrete IO-Link Hub Instruction Manual


Features



- Compact bimodal to IO-Link device converter that connects discrete inputs and sends the value to the IO-Link Master
- Outputs a discrete value as received from IO-Link Master Process Data Out
- Enabled Delay Modes: ON/OFF Delay, ON/OFF One-shot, ON/OFF/Retriggerable One-shot, ON/OFF Pulse-stretcher and Totalizer
- Measurement Metrics: Count, Events Per Minute (EPM), and Duration
- Discrete Mirroring: Discrete signals (In/Out) from all eight ports can be mirrored to any of the eight ports, Discrete Out, or the host white wire output
- Discrete input/output can be independently configured as NPN or PNP
- Rugged overmolded design meets IP65, IP67, and IP68
- Connects directly to a sensor or anywhere in-line for ease of use
- R95C IO-Link hubs are a quick, easy, and economical way to integrate non-IO-Link devices into an IO-Link system



Models



Overview

The R95C-8B22-KQ hub connects two discrete Input/Output channels to each of the eight unique ports, providing access to monitoring and configuring those ports with an IO-Link master. Host mirroring is available where a selected port input/output discrete signal can be routed to Pin 2 (male) on the PLC/Host connection.

Configuration

Figure 1 details the logic flow for each of the eight ports, while the tables define the configuration for each pin. For more information, see P/N 233583 R95C-8B22-KQ IO-Link Data Reference Guide and P/N 233584 R95C-8B22-KQ IODD Files.




Figure 1: Logic Flow

Table 1: Measurements – Female Pins

| Port 1-Port 8 Pin Number: Description | IO Metric | Description |
|--|-------------------------|---|
| Pin 4 – Discrete 1 Pin 2 – Discrete 2 | Count Value | Running count of the received input pulses |
| | Duration Value | Duration of the last input pulse in μs with 500 μs granularity |
| | Events per Minute Value | Running count of the number of pulses received averaged over one minute Range: 1 to 37,500 |
| | Reset Metrics | <ul style="list-style-type: none"> Do Not Reset Reset |

Table 2: Pin Configuration – Female Input

| Port 1-Port 8 Pin Number: Description | Name | Values |
|--|-----------------------------|--|
| Pin 4 – Discrete 1 Pin 2 – Discrete 2 | Discrete I/O Selection | <ul style="list-style-type: none"> NPN Input PNP Input NPN Output with Pull Up PNP Output with Pull Down NPN Output with Push/Pull PNP Output with Push/Pull |
| | Discrete Delay Mode | <ul style="list-style-type: none"> Disabled On/Off Delay On One-shot Off One-shot On Pulse-stretcher Off Pulse-stretcher Totalizer Retriggerable On One-shot Retriggerable Off One-shot |
| | Discrete Delay Timer 1 | Discrete On Delay, One-shot, Pulse-Stretcher Time, or Totalizer Count |
| | Discrete Delay Timer 2 | Discrete Off Delay or Totalizer Time |
| | Mirroring Enable | <ul style="list-style-type: none"> Disabled Enabled |
| | Mirroring Port Selection | <ul style="list-style-type: none"> Port 1 Port 2 Port 3 Port 4 Port 5 Port 6 Port 7 Port 8 |
| | Mirroring Channel Selection | <ul style="list-style-type: none"> Pin 4 – Discrete 1 Pin 2 – Discrete 2 |
| | Mirroring Inversion | <ul style="list-style-type: none"> Not Inverted Inverted |

Table 3: Pin Configuration – Male Output

| Pin Number: Description | Name | Values |
|---------------------------|----------------------------------|--|
| Pin 2 – Discrete Host Out | Host Mirroring Enable | <ul style="list-style-type: none"> Disabled Enabled |
| | Host Mirroring Port Selection | <ul style="list-style-type: none"> Port 1 Port 2 Port 3 Port 4 Port 5 Port 6 Port 7 Port 8 |
| | Host Mirroring Channel Selection | <ul style="list-style-type: none"> Pin 4 – Discrete 1 Pin 2 – Discrete 2 |
| | Host Mirroring Inversion | <ul style="list-style-type: none"> Not Inverted Inverted |
| | Host Mirroring Polarity | <ul style="list-style-type: none"> PNP NPN |
| | Host Mirroring Output Type | <ul style="list-style-type: none"> Open Collector Push/Pull |


IO-Link®

IO-Link® is a point-to-point communication link between a master device and a sensor and/or light. It can be used to automatically parameterize sensors or lights and to transmit process data. For the latest IO-Link protocol and specifications, please visit www.io-link.com.

For the latest IODD files, please refer to the Banner Engineering Corp website at: www.bannerengineering.com.

Mechanical Installation

Install the R95C to allow access for functional checks, maintenance, and service or replacement. Do not install the R95C in such a way to allow for intentional defeat. Fasteners must be of sufficient strength to guard against breakage. The use of permanent fasteners or locking hardware is recommended to prevent the loosening or displacement of the device. The mounting hole (4.5 mm) in the R95C accepts M4 (#8) hardware. See the figure below to help in determining the minimum screw length.



CAUTION: Do not overtighten the R95C's mounting screw during installation. Overtightening can affect the performance of the R95C.


Wiring

| Port 1-Port 8 — Female | Pin | Signal Description |
|------------------------|-----|---------------------|
| | 1 | 18 V DC to 30 V DC |
| | 2 | Discrete 2 (IN/OUT) |
| | 3 | Ground |
| | 4 | Discrete 1 (IN/OUT) |

| Male | Pin | Signal Description |
|------|-----|--------------------|
| | 1 | 18 V DC to 30 V DC |
| | 2 | Banner-specific |
| | 3 | Ground |
| | 4 | IO-Link |

Status Indicators

The R95C 8-Port 2-Channel Discrete Bimodal IO-Link Hub has two matching amber LED indicators, one for each channel, on both sides for each discrete device port to allow for installation needs and still provide adequate indication visibility. There is also an additional amber LED indicator on both sides of the converter, which is specific to the IO-Link communication.



| LED | Indication | Status |
|---------------------------------|--|--|
| Discrete Device Amber LEDs | Off | Discrete In and Out are inactive |
| | Solid Amber | Discrete In or Out is active |
| IO-Link Communication Amber LED | Off | IO-Link communications are not present |
| | Flashing Amber (900 ms On, 100 ms Off) | IO-Link communications are active |
| Power Indicator Green LED | Off | Power off |
| | Solid Green | Power on |

Specifications

Supply Voltage

18 V DC to 30 V DC at 400 mA maximum (exclusive of load)

Power Pass-Through Current

500 mA per port maximum

Discrete Output Load Rating

200 mA

Supply Protection Circuitry

Protected against reverse polarity and transient voltages

Leakage Current Immunity

400 µA

Indicators

Green: Power

Amber: IO-Link communications

Amber: 2x Discrete IN/OUT status

Connections

(8) Integral 4-pin M12 female quick disconnect

(1) Integral 4-pin M12 male quick-disconnect connector

Required Overcurrent Protection

WARNING: Electrical connections must be made by qualified personnel in accordance with local and national electrical codes and regulations.

Overcurrent protection is required to be provided by end product application per the supplied table.

Overcurrent protection may be provided with external fusing or via Current Limiting, Class 2 Power Supply.

Supply wiring leads < 24 AWG shall not be spliced.

For additional product support, go to www.bannerengineering.com.

| Supply Wiring (AWG) | Required Overcurrent Protection (A) | Supply Wiring (AWG) | Required Overcurrent Protection (A) |
|---------------------|-------------------------------------|---------------------|-------------------------------------|
| 20 | 5.0 | 26 | 1.0 |
| 22 | 3.0 | 28 | 0.8 |

| Supply Wiring (AWG) | Required Overcurrent Protection (A) | Supply Wiring (AWG) | Required Overcurrent Protection (A) |
|---------------------|-------------------------------------|---------------------|-------------------------------------|
| 24 | 1.0 | 30 | 0.5 |

Certifications



Banner Engineering BV
 Park Lane, Culliganlaan 2F
 bus 3, 1831 Diegem,
 BELGIUM



Turck Banner LTD Blenheim
 House, Blenheim Court, Wickford,
 Essex SS11 8YT, Great Britain



FCC Part 15 Class B

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.


Industry Canada

This device complies with CAN ICES-3 (B)/NMB-3(B). Operation is subject to the following two conditions: 1) This device may not cause harmful interference; and 2) This device must accept any interference received, including interference that may cause undesired operation.

Cet appareil est conforme à la norme NMB-3(B). Le fonctionnement est soumis aux deux conditions suivantes : (1) ce dispositif ne peut pas occasionner d'interférences, et (2) il doit tolérer toute interférence, y compris celles susceptibles de provoquer un fonctionnement non souhaité du dispositif.



Dimensions

All measurements are listed in millimeters [inches], unless noted otherwise.



Accessories

Cordsets

| 4-Pin Threaded M12 Cordsets—Double Ended | | | | |
|--|------------------|-------------------------------------|--|---|
| Model | Length | Style | Dimensions | Pinout |
| MQDEC-401SS | 0.31 m (1 ft) | Male Straight/Female Straight |  | Female |
| MQDEC-403SS | 0.91 m (2.99 ft) | | |  |
| MQDEC-406SS | 1.83 m (6 ft) | | | Male |
| MQDEC-412SS | 3.66 m (12 ft) | | |  |
| MQDEC-420SS | 6.10 m (20 ft) | | | <p>1 = Brown 2 = White 3 = Blue 4 = Black</p> |
| MQDEC-430SS | 9.14 m (30.2 ft) | | | |
| MQDEC-450SS | 15.2 m (49.9 ft) | | | |

Banner Engineering Corp. Limited Warranty

Banner Engineering Corp. warrants its products to be free from defects in material and workmanship for one year following the date of shipment. Banner Engineering Corp. will repair or replace, free of charge, any product of its manufacture which, at the time it is returned to the factory, is found to have been defective during the warranty period. This warranty does not cover damage or liability for misuse, abuse, or the improper application or installation of the Banner product.

THIS LIMITED WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES WHETHER EXPRESS OR IMPLIED (INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE), AND WHETHER ARISING UNDER COURSE OF PERFORMANCE, COURSE OF DEALING OR TRADE USAGE.

This Warranty is exclusive and limited to repair or, at the discretion of Banner Engineering Corp., replacement. **IN NO EVENT SHALL BANNER ENGINEERING CORP. BE LIABLE TO BUYER OR ANY OTHER PERSON OR ENTITY FOR ANY EXTRA COSTS, EXPENSES, LOSSES, LOSS OF PROFITS, OR ANY INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES RESULTING FROM ANY PRODUCT DEFECT OR FROM THE USE OR INABILITY TO USE THE PRODUCT, WHETHER ARISING IN CONTRACT OR WARRANTY, STATUTE, TORT, STRICT LIABILITY, NEGLIGENCE, OR OTHERWISE.**

Banner Engineering Corp. reserves the right to change, modify or improve the design of the product without assuming any obligations or liabilities relating to any product previously manufactured by Banner Engineering Corp. Any misuse, abuse, or improper application or installation of this product or use of the product for personal protection applications when the product is identified as not intended for such purposes will void the product warranty. Any modifications to this product without prior express approval by Banner Engineering Corp will void the product warranties. All specifications published in this document are subject to change; Banner reserves the right to modify product specifications or update documentation at any time. Specifications and product information in English supersede that which is provided in any other language. For the most recent version of any documentation, refer to: www.bannerengineering.com.

For patent information, see www.bannerengineering.com/patents.

Document title: R95C 8-Port 2-Channel Discrete Bimodal IO-Link Hub Instruction Manual

Part number: 233582

Revision: B

Original Instructions

© Banner Engineering Corp. All rights reserved.

